



# PS-2440T & PS-2480T

## ISOLATED CAMERA POWER SUPPLIES

**120V AC INPUT, 24 VOLT AC  
OUTPUT**

**4 AND 8 CAMERA MODELS**

**EACH OUTPUT POWERED BY A  
SEPARATE ISOLATED  
TRANSFORMER**

**UL LISTED MODELS**



Stealth camera power supplies provide a unique series of features which allow easier installation, greater reliability and unequalled flexibility. They are ideal in any multi-camera installation, avoiding the need to tie up one electrical outlet per camera, and provide significant advantages over multiple plug-in transformers in safety, convenience, neatness and cost.

### **Completely Isolated Transformer on Each Output**

Each output in the PS-2400T series is powered by a completely separate transformer. This avoids problems associated with ground loops in cameras without their own isolation transformer. Without this isolation, cameras can experience feedback and crosstalk caused by the ground loops.

### **Self-Resetting Fuse Protection**

All models include Stealth's self-restoring *SmartFuses*. These react like a glass fuse but reset themselves when the surge has passed or the fault is removed, eliminating costly service calls to replace blown fuses. Built-in surge suppression protects your cameras from transients. A roomy metal can allows plenty of space for wiring.

### **MODELS AVAILABLE**

**PS-2440T:** 4 Cameras Outputs

**PS-2440TUL:** 4 Camera Outputs, UL listed

**PS-2480T:** 8 Camera Outputs

**PS-2480TUL:** 4 Camera Outputs, UL listed

### **SPECIFICATIONS**

**Input Voltage:** 110 V AC (220V models available: add X to model number, e.g. PS-2440TX)

**Output Voltage:** 24 V AC, 500mA per Output

**SmartFuse Rating:** AC Models 1.85A, DC Models 1.1A

**Can Dimensions:** 8 Camera Models- 11 1/4 x 11 1/4 x 3 1/2 inches. 4 Camera Models 7 x 8 x 3 1/2 inches.

Wiring conforms with UL Class II requirements according to UL2044



600 Highland Avenue S.E., Hickory, NC 28601. Tel. 828-328-8674 Fax 828-328-1105 [www.stealthlabs.com](http://www.stealthlabs.com)